

# Eaton BR2020B100

Catalog Number: BR2020B100

Eaton BR style 1-inch loadcenter, main circuit breaker, no feed-thru lugs, 100A, single-phase, 20-pole, 20 circuits, 20 spaces, 120/240V, #4-1/0 AWG Cu/Al at 60°C or 75°C wire, NEMA 1 enclosure, c2 box size

## General specifications

Product Name	Catalog Number
Eaton BR main breaker loadcenter	BR2020B100
UPC	Product Length/Depth
786676444156	24.75 in
Product Height	Product Width
4.25 in	16 in
Product Weight	Warranty
23.49 lb	10 year
Certifications	
UL 67	
UL 50	



## Product specifications

### Number of spaces

20

### Special features

No feed-thru lugs

### Interrupt rating

10 kAIC

### Phase

Single-phase

### Wire size

#4-1/0 AWG Cu/Al

### Bus material

Aluminum

### Main circuit breaker

BR

### Enclosure

NEMA 1

### Amperage Rating

100 A

### Mounting

Combination

### Enclosure material

Metallic

### Type

Main circuit breaker

### Cover

Cover included

### Used with

Type BR 1-inch breakers

### Number of wires

3

### Number of circuits

20

### Voltage rating

120/240 V

### Box size

## Resources

### Brochures

[Loadcenters and Circuit Breakers](#)

[Type BR Arc Fault Circuit Breakers and Loadcenters](#)

### Catalogs

[Eaton's Volume 1—Residential and Light Commercial](#)

### Drawings

[Dimensional Drawing - BR 1 LOADCENTER, BR MAIN BREAKER, INDOOR NEMA 1, 120/240 VAC, 1 PHASE](#)

### Installation instructions

[Cutler-Hammer Type CH and BR Loadcenters - Instructions](#)

### Specifications and datasheets

[Eaton Specification Sheet - BR2020B100](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com  
© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)